DEVIALET INGÉNIERIE ACOUSTIQUE DE FRANCE

Software Manual

FIRMWARE 12.3.0 + DOS 2.2.2



RELEASE NOTE

DETAILS

Version number: Firmware 12.3.0 + DOS2.2.2

Release date: 11th June 2018

Compatible with: Expert Pro with Core Infinity

MAIN FEATURES

Existing features from	New features with	Feature to be activated
DOS 2.1.x	DOS 2.2.x	at a later stage
All physical inputs Configurator Devialet AIR* UPnP Renderer	Airplay* Spotify Connect	Bluetooth

BUG FIXES

Fixed issues from Firmware 12.1.2 + DOS 2.1.0

- Dual-mono: 176.4kHz playback not functional
- Dual-mono: analog inputs not functional on companion unit
- Dual-mono: RAM® settings not preserved upon restart
- Configurator: "default source at start-up" setting not functional
- Configurator: "fixed IP address" setting not functional
- USB: 'tick' noises with some Network players (e.g. Aurender)
- Network: device name annoucement not always consistent
- Network: conflict betwen Ethernet and Wi-Fi in some configurations
- Devialet Remote app: streaming sources appearing twice in source list

Fixed issues from Firmware 12.2.12 + DOS 2.2.0-beta14

- Roon/AIR: "Transport: Device in use" error message
- UPnP: device discovery not always consistent on network
- Network: network information not displayed in information menu

Remaining known issues

- Devialet AIR®: unstable playback on Windows with 50 ms latency
- Devialet AIR®: sporadic stability issue when switching sampling frequency
- Devialet Remote App: volume control inactive until stream is in progress
- USB: return channel not functional in 44.1kHz, 88.2kHz and 176.4kHz

Should you have any question, feedback or issues with this new software release, please contact support@devialet.com

How to update your Expert Pro

IMPORTANT: THIS UPDATE SHOULD TAKE APPROXIMATELY 5 MINUTES TO INSTALL. YOUR EXPERT PRO MUST NOT BE TURNED OFF DURING THE ENTIRE UPDATE PROCESS. WE STRONGLY RECOMMEND TO USE THE SD CARD SUPPLIED WITH YOUR EXPERT PRO.

To launch the update process of your Expert Pro, please follow the following steps:

- Eject the SD card from your Expert device and insert it in your computer. (NB: please make sure that the SD card is not in 'locked' position)
- 2. Open the SD card directory and empty it (you can save the dp_cfg.txt file separately).
- 3. Download the "FW12.3.0-DOS2.2.2.zip" release from your <u>Devialet online account.</u>
- Unzip the archive and copy/paste or drag-and-drop the 14 files on the SD card.(NB: please make sure that the files are at the root of the SD card and not in a folder)

NO NAME				
		Q Sea	irch	
Name	Date Modified	Size	Kind	
adh_04000000.hex	27 Oct 2017 at 13:15	31 KB	Document	
bl_msg.txt	27 Oct 2017 at 13:15	Zero bytes	Plain Text	
dos_4c4ccc3e.can	1 Jun 2018 at 16:12	60,1 MB	Document	
dspm08030000.hex	27 Oct 2017 at 13:15	122 KB	Document	
dspo01000000.hex	18 Oct 2017 at 12:30	41 KB	Document	
fpga06090000.hex	13 Apr 2018 at 11:22	391 KB	Document	
📄 fw.txt	1 Jun 2018 at 16:12	426 bytes	Plain Text	
i2s_03090000.hex	27 Oct 2017 at 13:15	57 KB	Document	
hm_12030000.hex	22 May 2018 at 11:25	750 KB	Document	
osca00200000.hex	15 May 2018 at 15:33	128 KB	Document	
psu_06040000.hex	27 Oct 2017 at 13:15	48 KB	Document	
README-EN.pdf	Today at 15:55	1,7 MB	PDF document	
README-FR.pdf	Today at 15:55	1,7 MB	PDF document	
usb_01020000.hex	9 Apr 2018 at 11:30	119 KB	Document	

- 5. Eject the SD card from your computer and insert it in your Expert device.(NB: if you want to update several units, please put the SD card in 'locked' position)
- 6. Put your Expert device in stand-by mode (screen off), and long press (5 seconds) the front button to operate a factory reset.(NB: if this does not work, unplug /plug your Expert device from the mains)
- 7. The update process should now start automatically. Once the update process is completed, the messages « Upgrade 12.3.0 successful » followed by « please press the front button » should appear on screen.
- 8. Your Expert Pro is now up-to-date with the Firmware 12.3.0 + DOS 2.2.2 release.

For more information or if you are having issues with this update process, please visit our <u>Help Center</u> or contact <u>support@devialet.com</u>

UPnP Renderer

HOW TO USE UPNP WITH YOUR EXPERT PRO?

To control your NAS drive from a third-party app using UPnP, please follow the steps below:

- 1. Setup your NAS on your local network by following the instructions provided by the manufacturer.
- 2. Download or open your favorite UPnP compatible app. *Please note that NAS manufacturers (QNAP, Synology...) usually have their own dedicated app (PC/Mac/Smartphone). If not provided by your NAS' manufacturer, you can still easily find many universal UPnP compatible apps that you can download to use that feature on Expert Pro.*
- 3. Select your "Devialet Expert Pro" system as the output device.
- 4. You can now browse your entire library and play any track on your Expert Pro.





HOW TO USE SPOTIFY CONNECT WITH YOUR EXPERT PRO?

The Spotify Connect technology lets you listen to your music on your Expert Pro connected to the Internet by using the Spotify app as a remote control (track selection, play/pause, volume control etc.). For more information, please visit https://www.spotify.com/connect/.

NOTES

- 1. A Spotify Premium account is required to use Spotify Connect.
- 2. Safety limit has been placed at -12dB when using your Spotify Connect. To control the volume more precisely and go beyond -12dB, please use the physical remote control of your Expert device.

INSTRUCTIONS

- 1. Make sure that your Expert Pro and your computer, tablet or smartphone are connected to the same network.
- Manually select the « Spotify » source on your Expert Pro, or simply go to the next step (an autoswitch feature will automatically select the "Spotify" source when you will try to connect Spotify with your Expert Pro).
- 3. Open the Spotify app on your smartphone, tablet or computer and start playing a track.
- 4. If you are using a computer, directly go to step 5. If you are using a smartphone or tablet, tap on the track that is being played at the bottom of your screen (cf. image A below) to get access to the playlist. Then tap on "Devices Available" at the bottom of your screen (cf. image B below).
- 5. On a computer, tap on the icon displaying a speaker located at the left of the volume bar.



- 6. On a smartphone or tablet, you can now see the devices compatible with Spotify Connect that are connected to your network (cf. image C below). Select your Expert device in the list and wait for the synchronisation to operate.
- 7. Your music should now be playing on your Expert Pro system.





HOW TO USE AIRPLAY® WITH YOUR EXPERT PRO?

The AirPlay® technology developed by Apple lets you wirelessly stream music and video content from an iOS device (iPhone, iPod touch or iPad), a Mac and a PC with iTunes straight to your Expert Pro.

NOTES

- 1. The AirPlay® protocol induces an initial standard 2-second latency when sending a command to your Expert Pro, with audio-to-video synchronization.
- 2. Safety limit has been placed at -12dB when using your Airplay device. To control the volume more precisely and go beyond -12dB, please use the physical remote control of your Expert device.

INSTRUCTIONS FROM AN IOS 11 DEVICE:

- 1. Make sure that your Expert and your tablet or smartphone are connected to the same network.
- 2. Start playing the track of your choice from any app on your iOS device.
- 3. Open the Control Center by swiping up. Then tap the top right hand corner of the music category (cf. image A).
- 4. Select your Expert device in the newly opened list (cf. image B).
- 5. Your music should now be playing on your Expert Pro system (cf. image C).



iOS 11 iPhone

INSTRUCTIONS FROM AN IOS 10 DEVICE:

- 1. Make sure that your Expert and your tablet or smartphone are connected to the same network.
- 2. Start playing the track of your choice from any app on your iOS device.
- 3. Open the Control Center by swiping up (cf. image A), then swipe the Control Center to the left to display the playlist (cf. image B).
- 4. If you are using an iPad, select your Expert device by tapping on its name (cf. image C).If you are using an iPhone, get access to the AirPlay compatible devices by tapping on "Now playing on iPhone".

iOS 10 iPad

IMAGE A	IMAGE B	IMAGE C
For V 137 134 224 January Paragraphic Paragraphic	No V DI	19 1 19 19 19 19 19 19 19 19 19 19 19 19
Arra Kateria Kateria	Lors Dates Approx	Arry Padrice Control C
In the second se	e e e e e e e e e e e e e e e e e e e	Contraction of the second seco
. •		
hard the second	Tanan maran	Conternational actions of the second
		•

INSTRUCTIONS FROM ITUNES ON A PC OR MAC:

- 1. Open iTunes and start playing any track.
- 2. Click on the icon located at the right of the volume slider and select your Expert device.

• • • • • •	→ — — ·	0:07 0:07	/ Gillespie-Gillespie-02,17		Q Rechercher
< >	Ordinateur AirPlay Livingroom	Our vous E Our vous E	Explorer Radio Store		Tout aléatoire 🗙 😶
Naylists de musique 🗸	61 <u>11</u> 5	Introduction by Dizzy Gillespie LIVE AT SINGER CONCERT HALL 1973	Dizzy Gillespie	2017 Jazz	2:15
Années 90 Les 25 plus écoutés	61 <u>115</u>	Sunshine LIVE AT SINGER CONCERT HALL 1973	Dizzy Gillespie (trumpet), Alex	. 2017 Jazz	19:00
Meilleur classement Morceaux récents	61 <u>115</u>	Announcement by Dizzy Gillespie LIVE AT SINGER CONCERT HALL 1973	Dizzy Gillespie	2017 Jazz	0:43
🗱 Musique classique 🗐 Brubeck	01 <u>115</u>	Brother K LIVE AT SINGER CONCERT HALL 1973	Dizzy Gillespie (trumpet), Alex	. 2017 Jazz	11:30
Fitzgerald Gillespie	61 <u>115</u>	Announcement by Dizzy Gillespie LIVE AT SINGER CONCERT HALL 1973	Dizzy Gillespie	2017 Jazz	0:16
	CILLS	Ole for the Gypsies LIVE AT SINGER CONCERT HALL 1973	Dizzy Gillespie (trumpet), Alex	. 2017 Jazz	15:58
	Announcement by Dizzy Gillespie LIVE AT SINGER CONCERT HALL 1973	Dizzy Gillespie	2017 Jazz	0:49	
	The Truth LIVE AT SINGER CONCERT HALL 1973	Dizzy Gillespie (trumpet), Alex	. 2017 Jazz	9:12	
	61 <u>1.5</u>	Manteca LIVE AT SINGER CONCERT HALL 1973	Dizzy Gillespie (trumpet), Alex	. 2017 Jazz	10:07
	01 <u>11</u> 2	The Blues LIVE AT SINGER CONCERT HALL 1973	Dizzy Gillespie (trumpet, vocal.	. 2017 Jazz	8:36